SIEMENS

Data sheet

6ES7313-6CG04-0AB0



SIMATIC S7-300, CPU 313C-2 DP Compact CPU with MPI, 16 DI/16 DO, 3 high-speed counters (30 kHz), integrated DP interface, Integr. power supply 24 V DC, work memory 128 KB, Front connector (1x 40-pole) and Micro Memory Card required

General information	
HW functional status	01
Firmware version	V3.3
Engineering with	
 Programming package 	STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP 203
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
external protection for power supply lines (recommendation)	Miniature circuit breaker, type C; min. 2 A; miniature circuit breaker type B, min. 4 A
Mains buffering	
 Mains/voltage failure stored energy time 	5 ms
Repeat rate, min.	1 s
Load voltage L+	
Digital inputs	
— Rated value (DC)	24 V
 Reverse polarity protection 	Yes
Digital outputs	
— Rated value (DC)	24 V
 Reverse polarity protection 	No
Input current	
Current consumption (rated value)	800 mA
Current consumption (in no-load operation), typ.	110 mA
Inrush current, typ.	5 A
² t	0.7 A ² ·s
Digital inputs	
 from load voltage L+ (without load), max. 	80 mA
Digital outputs	
 from load voltage L+, max. 	50 mA
Power loss	
Power loss, typ.	9 W
Memory	
Work memory	400 lb.t.
integrated	128 kbyte
• expandable	No
Load memory	Vaa
Plug-in (MMC) Plug in (MMC) max	Yes
 Plug-in (MMC), max. Data management on MMC (after last 	8 Mbyte 10 a
 Data management on MMC (after last 	iv a

programming), min.	
Backup	
• present	Yes; Guaranteed by MMC (maintenance-free)
without battery	Yes; Program and data
CPU processing times	
for bit operations, typ.	0.07 μs
for word operations, typ.	0.15 µs
for fixed point arithmetic, typ.	0.2 µs
for floating point arithmetic, typ.	0.72 µs
CPU-blocks	
Number of blocks (total)	1 024; (DBs, FCs, FBs); the maximum number of loadable blocks can
	be reduced by the MMC used.
DB	
 Number, max. 	1 024; Number range: 1 to 16000
 Size, max. 	64 kbyte
FB	
Number, max.	1 024; Number range: 0 to 7999
• Size, max.	64 kbyte
FC	
Number, max.	1 024; Number range: 0 to 7999
• Size, max.	64 kbyte
OB	
Number, max.	see instruction list
• Size, max.	64 kbyte
 Number of free cycle OBs 	1; OB 1
 Number of time alarm OBs 	1; OB 10
 Number of delay alarm OBs 	2; OB 20, 21
 Number of cyclic interrupt OBs 	4; OB 32, 33, 34, 35
 Number of process alarm OBs 	1; OB 40
 Number of DPV1 alarm OBs 	3; OB 55, 56, 57
 Number of startup OBs 	1; OB 100
 Number of asynchronous error OBs 	5; OB 80, 82, 85, 86, 87
 Number of synchronous error OBs 	2; OB 121, 122
Nesting depth	
 per priority class 	16
 additional within an error OB 	4
Counters, timers and their retentivity	
S7 counter	
Number	256
Retentivity	
— adjustable	Yes
— lower limit	0
— upper limit	255
— preset	Z 0 to Z 7
Counting range	
— lower limit	0
— upper limit	999
IEC counter	
present	Yes
• Туре	SFB
Number	Unlimited (limited only by RAM capacity)
S7 times	
Number	256
Retentivity	
— adjustable	Yes
— lower limit	0
— upper limit	255
— preset	No retentivity
Time range	
— lower limit	10 ms
— upper limit	9 990 s
IEC timer	
present	Yes

• Туре	SFB
• Number	Unlimited (limited only by RAM capacity)
Data areas and their retentivity	
Retentive data area (incl. timers, counters, flags), max.	64 kbyte
Flag	
• Size, max.	256 byte
Retentivity available	Yes; MB 0 to MB 255
 Retentivity preset 	MB 0 to MB 15
Number of clock memories	8; 1 memory byte
Data blocks	
Retentivity adjustable	Yes; via non-retain property on DB
Retentivity preset	Yes
Local data	22 kbyte: May 2018 bytes per black
per priority class, max. Address area	32 kbyte; Max. 2048 bytes per block
I/O address area • Inputs	2.048 hyto
Outputs	2 048 byte 2 048 byte
of which distributed	2 040 byte
— Inputs	2 030 byte
— Outputs	2 030 byte
Process image	
Inputs	2 048 byte
Outputs	2 048 byte
 Inputs, adjustable 	2 048 byte
 Outputs, adjustable 	2 048 byte
 Inputs, default 	128 byte
Outputs, default	128 byte
Default addresses of the integrated channels	
— Digital inputs	124.0 to 125.7
— Digital outputs Digital channels	124.0 to 125.7
Inputs	16 256
- of which central	1 008
Outputs	16 256
— of which central	1 008
Analog channels	
Inputs	1 015
— of which central	248
Outputs	1 015
— of which central	248
Hardware configuration	
Number of expansion units, max.	3
Number of DP masters	
• integrated	1
via CP Number of operable FMs and CPs (recommended)	4
• FM	8
• CP, PtP	8
• CP, LAN	6
Rack	
• Racks, max.	4
Modules per rack, max.	8; In rack 3 max. 7
Time of day	
Clock	
Hardware clock (real-time)	Yes
retentive and synchronizable	Yes
Backup time	6 wk; At 40 °C ambient temperature
 Deviation per day, max. 	10 s; Typ.: 2 s
 Behavior of the clock following POWER-ON 	Clock continues running after POWER OFF
 Behavior of the clock following expiry of backup 	the clock continues at the time of day it had when power was switched
period	off
Operating hours counter	

Subject to change without notice © Copyright Siemens

• Number	1
Number/Number range	
Range of values	0 to 2^31 hours (when using SFC 101)
Granularity	1 h Mars Must be reached at a sharehout
retentive Clock synchronization	Yes; Must be restarted at each restart
supported	Yes
• to MPI, master	Yes
• to MPI, slave	Yes
• to DP, master	Yes; With DP slave only slave clock
• to DP, slave	Yes
• in AS, master	Yes
• in AS, slave	No
Digital inputs	
Number of digital inputs	16
of which inputs usable for technological functions	12
integrated channels (DI)	16
Input characteristic curve in accordance with IEC 61131,	Yes
type 1	
Number of simultaneously controllable inputs	
horizontal installation	
— up to 40 °C, max.	16
— up to 60 °C, max.	8
vertical installation	
— up to 40 °C, max.	8
Input voltage	
 Rated value (DC) 	24 V
• for signal "0"	-3 to +5V
• for signal "1"	+15 to +30 V
Input current	2.4
• for signal "1", typ.	8 mA
Input delay (for rated value of input voltage)	
for standard inputs	Yes; 0.1 / 0.3 / 3 / 15 ms (You can reconfigure the input delay of the
— parameterizable	standard inputs during program runtime. Please note that under certain circumstances your newly set filter time may not be effective until the next filter cycle.)
— Rated value	3 ms
— Rated value for technological functions	3 ms
	3 ms 16 µs; Minimum pulse width/minimum pause between pulses at maximum counting frequency
for technological functions	16 µs; Minimum pulse width/minimum pause between pulses at
for technological functions — at "0" to "1", max.	16 µs; Minimum pulse width/minimum pause between pulses at
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max.	16 μs; Minimum pulse width/minimum pause between pulses at maximum counting frequency
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions	 16 μs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max.	 16 μs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max. — unshielded, max.	 16 μs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max.	 16 μs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max. — unshielded, max.	 16 μs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max. — unshielded, max. — unshielded, max. — unshielded, max. — or shielded, max. — unshielded, max. — unshielded, max. — of which high-speed outputs	 16 µs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency not allowed 16 4; Notice: You cannot connect the fast outputs of your CPU in parallel
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max. — unshielded, max. Digital outputs Number of digital outputs • of which high-speed outputs integrated channels (DO)	 16 µs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency not allowed 16 4; Notice: You cannot connect the fast outputs of your CPU in parallel 16
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max. — unshielded, max. — unshielded, max. Digital outputs Number of digital outputs • of which high-speed outputs integrated channels (DO) Short-circuit protection	 16 µs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency not allowed 16 4; Notice: You cannot connect the fast outputs of your CPU in parallel 16 Yes; Clocked electronically
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max. — unshielded, max. Digital outputs Number of digital outputs • of which high-speed outputs integrated channels (DO) Short-circuit protection • Response threshold, typ.	 16 µs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency not allowed 16 4; Notice: You cannot connect the fast outputs of your CPU in parallel 16 Yes; Clocked electronically 1 A
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max. — unshielded, max. Digital outputs Number of digital outputs • of which high-speed outputs integrated channels (DO) Short-circuit protection • Response threshold, typ. Limitation of inductive shutdown voltage to	 16 µs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency not allowed 16 4; Notice: You cannot connect the fast outputs of your CPU in parallel 16 Yes; Clocked electronically 1 A L+ (-48 V)
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max. — unshielded, max. Digital outputs Number of digital outputs • of which high-speed outputs integrated channels (DO) Short-circuit protection • Response threshold, typ. Limitation of inductive shutdown voltage to Controlling a digital input	 16 µs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency not allowed 16 4; Notice: You cannot connect the fast outputs of your CPU in parallel 16 Yes; Clocked electronically 1 A
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max. — unshielded, max. — unshielded, max. — unshielded, max. Digital outputs Number of digital outputs • of which high-speed outputs integrated channels (DO) Short-circuit protection • Response threshold, typ. Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs	 16 µs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency not allowed 16 4; Notice: You cannot connect the fast outputs of your CPU in parallel 16 Yes; Clocked electronically 1 A L+ (-48 V) Yes
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max. — unshielded, max. — unshielded, max. — unshielded, max. Digital outputs Number of digital outputs • of which high-speed outputs integrated channels (DO) Short-circuit protection • Response threshold, typ. Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • on lamp load, max.	 16 µs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency not allowed 16 4; Notice: You cannot connect the fast outputs of your CPU in parallel 16 Yes; Clocked electronically 1 A L+ (-48 V)
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max. — unshielded, max. — unshielded, max. — unshielded, max. Digital outputs Number of digital outputs • of which high-speed outputs integrated channels (DO) Short-circuit protection • Response threshold, typ. Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • on lamp load, max. Load resistance range	 16 µs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency not allowed 16 4; Notice: You cannot connect the fast outputs of your CPU in parallel 16 Yes; Clocked electronically 1 A L+ (-48 V) Yes 5 W
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max. — unshielded, max. — unshielded, max. Digital outputs Number of digital outputs • of which high-speed outputs integrated channels (DO) Short-circuit protection • Response threshold, typ. Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • on lamp load, max. Load resistance range • lower limit	16 μs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency not allowed 16 4; Notice: You cannot connect the fast outputs of your CPU in parallel 16 Yes; Clocked electronically 1 A L+ (-48 V) Yes 5 W 48 Ω
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max. — unshielded, max. — unshielded, max. Digital outputs Number of digital outputs • of which high-speed outputs integrated channels (DO) Short-circuit protection • Response threshold, typ. Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • on lamp load, max. Load resistance range • lower limit • upper limit	 16 µs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency not allowed 16 4; Notice: You cannot connect the fast outputs of your CPU in parallel 16 Yes; Clocked electronically 1 A L+ (-48 V) Yes 5 W
for technological functions 	16 μs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency not allowed 16 4; Notice: You cannot connect the fast outputs of your CPU in parallel 16 Yes; Clocked electronically 1 A L+ (-48 V) Yes 5 W 48 Ω 4 kΩ
for technological functions — at "0" to "1", max. Cable length • shielded, max. • unshielded, max. for technological functions — shielded, max. — unshielded, max. — unshielded, max. Digital outputs Number of digital outputs • of which high-speed outputs integrated channels (DO) Short-circuit protection • Response threshold, typ. Limitation of inductive shutdown voltage to Controlling a digital input Switching capacity of the outputs • on lamp load, max. Load resistance range • lower limit • upper limit Output voltage • for signal "1", min.	16 μs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency not allowed 16 4; Notice: You cannot connect the fast outputs of your CPU in parallel 16 Yes; Clocked electronically 1 A L+ (-48 V) Yes 5 W 48 Ω
for technological functions 	16 μs; Minimum pulse width/minimum pause between pulses at maximum counting frequency 1 000 m; 100 m for technological functions 600 m; for technological functions: No 100 m; at maximum count frequency not allowed 16 4; Notice: You cannot connect the fast outputs of your CPU in parallel 16 Yes; Clocked electronically 1 A L+ (-48 V) Yes 5 W 48 Ω 4 kΩ

 for signal "1" permissible range, min. 	5 mA
 for signal "1" permissible range, max. 	0.6 A
 for signal "1" minimum load current 	5 mA
 for signal "0" residual current, max. 	0.5 mA
Parallel switching of two outputs	
 for uprating 	No
 for redundant control of a load 	Yes
Switching frequency	
 with resistive load, max. 	100 Hz
 with inductive load, max. 	0.5 Hz
 on lamp load, max. 	100 Hz
 of the pulse outputs, with resistive load, max. 	2.5 kHz
Total current of the outputs (per group)	
horizontal installation	
— up to 40 °C, max.	3 A
— up to 60 °C, max.	2 A
vertical installation	
— up to 40 °C, max.	2 A
Cable length	4.000
shielded, max.	1 000 m
• unshielded, max.	600 m
Analog inputs	
Number of analog inputs	0
integrated channels (AI)	0
Analog outputs	
Number of analog outputs	0
integrated channels (AO)	0
Encoder	
Connectable encoders	
2-wire sensor	Yes
— permissible quiescent current (2-wire sensor),	1.5 mA
max.	
max. Interfaces	
max.	0 0
max. Interfaces Number of industrial Ethernet interfaces	0
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces	0 0
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces	0 0 2; MPI and PROFIBUS DP
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces 1. Interface	0 0 2; MPI and PROFIBUS DP 0
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces I. Interface Interface type Isolated	0 0 2; MPI and PROFIBUS DP 0
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types • RS 485	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface Interface type Isolated Interface types • RS 485 • Output current of the interface, max.	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types • RS 485 • Output current of the interface, max. Protocols	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types • RS 485 • Output current of the interface, max. Protocols • MPI	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types • RS 485 • Output current of the interface, max. Protocols • MPI • PROFIBUS DP master	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types • RS 485 • Output current of the interface, max. Protocols • MPI • PROFIBUS DP master • PROFIBUS DP slave	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No No No
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types • RS 485 • Output current of the interface, max. Protocols • MPI • PROFIBUS DP master	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types • RS 485 • Output current of the interface, max. Protocols • MPI • PROFIBUS DP master • PROFIBUS DP slave • Point-to-point connection MPI	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No No No
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types • RS 485 • Output current of the interface, max. Protocols • MPI • PROFIBUS DP master • PROFIBUS DP slave • Point-to-point connection	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No No No No
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types RS 485 Output current of the interface, max. Protocols MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection MPI Transmission rate, max.	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No No No No
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types • RS 485 • Output current of the interface, max. Protocols • MPI • PROFIBUS DP master • PROFIBUS DP slave • Point-to-point connection MPI • Transmission rate, max. Services	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No No No No No
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types • RS 485 • Output current of the interface, max. Protocols • MPI • PROFIBUS DP master • PROFIBUS DP slave • Point-to-point connection MPI • Transmission rate, max. Services - PG/OP communication	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No No No No No No Yes
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface Interface type Isolated Interface types RS 485 Output current of the interface, max. Protocols MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection MPI Transmission rate, max. Services PG/OP communication PROting	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No No No No No No
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types RS 485 Output current of the interface, max. Protocols MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection MPI Transmission rate, max. Services PG/OP communication Routing Global data communication	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No No No No No No No
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types RS 485 Output current of the interface, max. Protocols MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection MPI Transmission rate, max. Services PG/OP communication Routing Global data communication S7 basic communication S7 basic communication	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No No No No No Yes Yes Yes Yes Yes
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types RS 485 Output current of the interface, max. Protocols MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection MPI Transmission rate, max. Services PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication S7 communication	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No No No No No No No No No No
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types RS 485 Output current of the interface, max. Protocols MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection MPI Transmission rate, max. Services PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No No No No No No No No No No
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types RS 485 Output current of the interface, max. Protocols NPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection MPI Transmission rate, max. Services PG/OP communication Routing Global data communication S7 basic communication S7 communication, as client S7 communication, as server Interface	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No No No No No 187.5 kbit/s Yes Yes Yes Yes Yes Yes Yes Ye
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types RS 485 Output current of the interface, max. Protocols MPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection MPI Transmission rate, max. Services PG/OP communication Routing Global data communication S7 basic communication S7 communication, as client S7 communication, as server Interface type Interface type Interface type	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No No No No No 187.5 kbit/s Yes Yes Yes Yes Yes Yes Yes Ye
max. Interfaces Number of industrial Ethernet interfaces Number of PROFINET interfaces Number of RS 485 interfaces Number of RS 422 interfaces Interface Interface type Isolated Interface types RS 485 Output current of the interface, max. Protocols NPI PROFIBUS DP master PROFIBUS DP slave Point-to-point connection MPI Transmission rate, max. Services PG/OP communication Routing Global data communication S7 basic communication S7 communication, as client S7 communication, as server Interface	0 0 2; MPI and PROFIBUS DP 0 Integrated RS 485 interface No Yes 200 mA Yes No No No No No 187.5 kbit/s Yes Yes Yes Yes Yes Yes Yes Ye

Subject to change without notice © Copyright Siemens

• RS 485	Yes
Output current of the interface, max.	200 mA
Protocols	200 117
• MPI	No
PROFINET IO Controller	No
PROFINET IO Device	No
PROFINET TO Device PROFINET CBA	No
PROFINE I CBA PROFIBUS DP master	Yes
PROFIBUS DP slave	Yes
PROFIBUS DP master	
Transmission rate, max.	12 Mbit/s
Number of DP slaves, max.	124
Services	M
- PG/OP communication	Yes
— Routing	Yes
— Global data communication	No
— S7 basic communication	Yes; I blocks only
— S7 communication	Yes; Yes (only server; connection configured at one end)
— S7 communication, as client	No
— S7 communication, as server	Yes
— Equidistance	Yes
 — Isochronous mode 	No
- SYNC/FREEZE	Yes
 Activation/deactivation of DP slaves 	Yes
 — Number of DP slaves that can be 	8
simultaneously activated/deactivated, max.	
— Direct data exchange (slave-to-slave	Yes; as subscriber
communication)	
— DPV1	Yes
Address area	
— Inputs, max.	2 kbyte
— Outputs, max.	2 kbyte
User data per DP slave	
— Inputs, max.	244 byte
— Outputs, max.	244 byte
PROFIBUS DP slave	
• GSD file	The latest GSD file is available on the Internet
– · · · ·	(http://www.siemens.com/profibus-gsd)
Transmission rate, max.	12 Mbit/s
automatic baud rate search	Yes; only with passive interface
Address area, max.	32
 User data per address area, max. 	
	32 byte
Services	
— PG/OP communication	Yes
 PG/OP communication Routing 	Yes Yes; Only with active interface
 — PG/OP communication — Routing — Global data communication 	Yes Yes; Only with active interface No
 PG/OP communication Routing Global data communication S7 basic communication 	Yes Yes; Only with active interface No No
 PG/OP communication Routing Global data communication S7 basic communication S7 communication 	Yes Yes; Only with active interface No
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client 	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server 	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end)
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server Direct data exchange (slave-to-slave) 	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server Direct data exchange (slave-to-slave communication) 	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No Yes Yes
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server Direct data exchange (slave-to-slave communication) DPV1 	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No Yes
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server Direct data exchange (slave-to-slave communication) DPV1 Transfer memory 	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No Yes Yes No
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server Direct data exchange (slave-to-slave communication) DPV1 Transfer memory Inputs 	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No Yes Yes No 244 byte
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server Direct data exchange (slave-to-slave communication) DPV1 Transfer memory 	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No Yes Yes No
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server Direct data exchange (slave-to-slave communication) DPV1 Transfer memory Inputs 	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No Yes Yes No 244 byte
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server Direct data exchange (slave-to-slave communication) DPV1 Transfer memory Inputs Outputs 	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No Yes Yes No 244 byte
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server Direct data exchange (slave-to-slave communication) DPV1 Transfer memory Inputs Outputs Protocols PROFIsafe	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No Yes Yes No 244 byte 244 byte
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server Direct data exchange (slave-to-slave communication) DPV1 Transfer memory Inputs Outputs PROFIsafe communication functions / header 	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No Yes Yes Yes No 244 byte 244 byte 244 byte
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server Direct data exchange (slave-to-slave communication) DPV1 Transfer memory Inputs Outputs Protocols PROFIsafe communication functions / header PG/OP communication	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No Yes Yes Yes No 244 byte 244 byte 244 byte 245 Yes
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server Direct data exchange (slave-to-slave communication) DPV1 Transfer memory Inputs Outputs Protocols PROFIsafe communication functions / header PG/OP communication	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No Yes Yes Yes No 244 byte 244 byte 244 byte
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server Direct data exchange (slave-to-slave communication) DPV1 Transfer memory Inputs Outputs Protocols PROFIsafe communication functions / header PG/OP communication Global data communication 	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No Yes Yes No 244 byte 244 byte 244 byte Yes No
 PG/OP communication Routing Global data communication S7 basic communication S7 communication S7 communication, as client S7 communication, as server Direct data exchange (slave-to-slave communication) DPV1 Transfer memory Inputs Outputs Protocols PROFIsafe communication functions / header PG/OP communication	Yes Yes; Only with active interface No No Yes; Yes (only server; connection configured at one end) No Yes Yes Yes No 244 byte 244 byte 244 byte 245 Yes

 Number of GD packets, max. 	8
 Number of GD packets, transmitter, max. 	8
Number of GD packets, receiver, max.	8
 Size of GD packets, max. 	22 byte
Size of GD packet (of which consistent), max.	22 byte
S7 basic communication	
• supported	Yes
• User data per job, max.	76 byte
 User data per job (of which consistent), max. 	76 byte; 76 bytes (with X_SEND or X_RCV); 64 bytes (with X_PUT or X_GET as server)
S7 communication	
supported	Yes
• as server	Yes
• as client	Yes; Via CP and loadable FB
 User data per job, max. 	180 kbyte; With PUT/GET
 User data per job (of which consistent), max. 	240 byte; as server
S5 compatible communication	
• supported	Yes; via CP and loadable FC
Number of connections	
overall	8
 usable for PG communication 	7
- reserved for PG communication	1
— adjustable for PG communication, min.	1
 adjustable for PG communication, max. 	7
 usable for OP communication 	7
 reserved for OP communication 	1
 — adjustable for OP communication, min. 	1
 — adjustable for OP communication, max. 	7
 usable for S7 basic communication 	4
 reserved for S7 basic communication 	0
 — adjustable for S7 basic communication, min. 	0
 — adjustable for S7 basic communication, max. 	4
 usable for routing 	4; max.
5	.,
S7 message functions	
5	8; Depending on the configured connections for PG/OP and S7 basic communication
S7 message functions Number of login stations for message functions, max. Process diagnostic messages	8; Depending on the configured connections for PG/OP and S7 basic communication Yes
S7 message functions Number of login stations for message functions, max.	8; Depending on the configured connections for PG/OP and S7 basic communication
S7 message functions Number of login stations for message functions, max. Process diagnostic messages	8; Depending on the configured connections for PG/OP and S7 basic communication Yes
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max.	8; Depending on the configured connections for PG/OP and S7 basic communication Yes
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max.	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes 1nputs, outputs, memory bits, DB, times, counters 30
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. — of which status variables, max.	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max.	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes 1nputs, outputs, memory bits, DB, times, counters 30
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max. — of which control variables, max. — of which control variables, max.	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max.	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max. — of which status variables, max. — of which control variables, max. — of which status variables, max. — of which control variables, max.	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. of which status variables, max. of which control variables, max. of which control variables, max. of which status variables, max. of which control variables, max.	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max. — of which control variables, max. Berocing • Forcing • Forcing • Number of variables, max.	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max. — of which control variables, max. Berocing • Forcing • Forcing • Forcing • Number of variables, max. Diagnostic buffer • present	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max. — of which control variables, max. Berocing • Forcing • Forcing • Forcing, variables • Number of variables, max. Diagnostic buffer • present • Number of entries, max.	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes 500
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max. — of which control variables, max. — of which status variables, max. — of which control variables, max. — of which control variables, max. — of which control variables, max. — of variables • Number of variables, max. — present • Number of entries, max. — adjustable	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes S00 No
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max. — of which control variables, max. — of which status variables, max. — of which control variables, max. Diagnostic buffer • present • Number of entries, max. — adjustable — of which powerfail-proof	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes S00 No 100; Only the last 100 entries are retained
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max. — of which control variables, max. — of which control variables, max. — of which status variables, max. — of which control variables, max. — of which control variables, max. — of which control variables, max. Diagnostic buffer • present • Number of entries, max. — adjustable — of which powerfail-proof • Number of entries readable in RUN, max.	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes S00 No 100; Only the last 100 entries are retained 499
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. of which status variables, max. of which control variables, max. of which status variables, max. of which control variables, max. of which control variables, max. Diagnostic buffer • present • Number of entries, max. adjustable of which powerfail-proof • Number of entries readable in RUN, max. adjustable	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes S00 No 100; Only the last 100 entries are retained 499 Yes; From 10 to 499
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. - of which status variables, max. - of which control variables, max. Diagnostic buffer • present • Number of entries, max. - adjustable - of which powerfail-proof • Number of entries readable in RUN, max. - adjustable - preset	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes S00 No 100; Only the last 100 entries are retained 499
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. of which status variables, max. of which control variables, max. of which status variables, max. of which control variables, max. of which control variables, max. Diagnostic buffer • present • Number of entries, max. adjustable of which powerfail-proof • Number of entries readable in RUN, max. adjustable	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes S00 No 100; Only the last 100 entries are retained 499 Yes; From 10 to 499
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. — of which status variables, max. — of which control variables, max. — of which powerfail-proof • Number of entries, max. — adjustable — of which powerfail-proof • Number of entries readable in RUN, max. — adjustable — preset Service data • can be read out	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes 500 No 100; Only the last 100 entries are retained 499 Yes; From 10 to 499 10
S7 message functions Number of login stations for message functions, max. Process diagnostic messages simultaneously active Alarm-S blocks, max. Test commissioning functions Status block Single step Number of breakpoints Status/control • Status/control variable • Variables • Number of variables, max. - of which status variables, max. - of which control variables, max. - of which control variables, max. - of which status variables, max. Berocing • Forcing • Forcing • Forcing • Forcing, variables • Number of entries, max. - adjustable - of which powerfail-proof • Number of entries readable in RUN, max. - adjustable - preset Service data	8; Depending on the configured connections for PG/OP and S7 basic communication Yes 300 Yes; Up to 2 simultaneously Yes 4 Yes Inputs, outputs, memory bits, DB, times, counters 30 30 14 Yes Inputs, outputs 10 Yes 500 No 100; Only the last 100 entries are retained 499 Yes; From 10 to 499 10

 Status indicator digital input (green) 	Yes
Status indicator digital output (green)	Yes
Integrated Functions	100
	Yes
Frequency measurement Number of frequency meters 	
	3; up to 30 kHz (see "Technological Functions" manual)
controlled positioning	No
integrated function blocks (closed-loop control)	Yes; PID controller (see "Technological Functions" manual)
PID controller	Yes
Number of pulse outputs	3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual)
Limit frequency (pulse)	2.5 kHz
Potential separation	2.5 NH2
Potential separation digital inputs	No.
Potential separation digital inputs	Yes
between the channels	No
between the channels and backplane bus	Yes
Potential separation digital outputs	N .
Potential separation digital outputs	Yes
between the channels	Yes
between the channels, in groups of	8
 between the channels and backplane bus 	Yes
Isolation	
Isolation tested with	600 V DC
Ambient conditions	
Ambient temperature during operation	
• min.	0 °C
• max.	60 °C
configuration / header	
Configuration software	
Configuration software	Yes: STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with
Configuration software • STEP 7	Yes; STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP 203
•	
STEP 7 STEP 7 Lite	HSP 203
• STEP 7	HSP 203
STEP 7 STEP 7 Lite configuration / programming / header Command set	HSP 203 No
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels	HSP 203 No see instruction list
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC)	HSP 203 No see instruction list 8
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB)	HSP 203 No see instruction list 8 see instruction list
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language	HSP 203 No see instruction list 8 see instruction list see instruction list
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language — LAD	HSP 203 No see instruction list 8 see instruction list see instruction list
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language — LAD — FBD	HSP 203 No see instruction list 8 see instruction list see instruction list Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language — LAD — FBD — STL	HSP 203 No see instruction list 8 see instruction list see instruction list Yes Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language — LAD — FBD — STL — SCL	HSP 203 No see instruction list 8 see instruction list see instruction list Yes Yes Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language — LAD — FBD — STL — SCL — CFC	HSP 203 No see instruction list 8 see instruction list see instruction list Yes Yes Yes Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language — LAD — FBD — STL — SCL — CFC — GRAPH	HSP 203 No see instruction list 8 see instruction list see instruction list Yes Yes Yes Yes Yes Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language — LAD — FBD — STL — SCL — CFC — GRAPH — HiGraph®	HSP 203 No see instruction list 8 see instruction list see instruction list Yes Yes Yes Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language LAD FBD STL SCL	HSP 203 No see instruction list 8 see instruction list see instruction list Yes Yes Yes Yes Yes Yes Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set System functions (SFC) System function blocks (SFB) Programming language — LAD — FBD — STL — SCL — CFC — GRAPH — HiGraph® Know-how protection User program protection/password protection	HSP 203 No see instruction list 8 see instruction list see instruction list Yes Yes Yes Yes Yes Yes Yes Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language	HSP 203 No see instruction list 8 see instruction list see instruction list Yes Yes Yes Yes Yes Yes Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language LAD FBD STL SCL SCL CFC GRAPH HiGraph® Know-how protection Sustem protection/password protection Block encryption Dimensions	HSP 203 No see instruction list 8 see instruction list Yes Yes Yes Yes Yes Yes Yes Yes Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set Source Nesting levels System functions (SFC) System function blocks (SFB) Programming language	HSP 203 No see instruction list 8 see instruction list see instruction list Yes Yes Yes Yes Yes Yes Yes Yes Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set Source Nesting levels System functions (SFC) System function blocks (SFB) Programming language	HSP 203 No see instruction list 8 see instruction list see instruction list Yes Yes Yes Yes Yes Yes Yes Yes Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language	HSP 203 No see instruction list 8 see instruction list see instruction list Yes Yes Yes Yes Yes Yes Yes Yes Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language	HSP 203 No see instruction list 8 see instruction list 9 Yes Yes Yes Yes Yes Yes Yes Yes Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language	HSP 203 No see instruction list 8 see instruction list see instruction list Yes Yes Yes Yes Yes Yes Yes Yes Yes Yes
STEP 7 STEP 7 Lite configuration / programming / header Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language	HSP 203 No see instruction list 8 see instruction list 9 Yes Yes Yes Yes Yes Yes Yes Yes Yes Yes